

# AC-515M

*Battery buffered siren with softchirp*

The siren makes alarm in case that car battery is disconnected by an act of sabotage or manipulation.



It is possible to switch the siren off with key. That is necessary for sample if a workshop has to disconnect the car battery to work at car.

Two Key will be delivered with the siren.

## Wire colors

Red = +12V – If not connected or 0V the siren gives acoustic alarm  
Black = Ground  
White = Siren active if +12 Volt is switched to white wire. (connect with TEC pink/black)  
Blue = Siren active if Ground is switched to the blue wire

It is possible to use white **or** blue wire. **Never use both wires at same time!**

## Technical Data

Voltage range	9V – 16V
Current in alarm state	600mA
Power	20W
Temperature range	-30°C bis +80°C
Weight with wires	
Dimension of the housing	77 x 57 x 57 mm
Internal battery	Ni-Mh

## notices

**When installing electrical assemblies in vehicles, please generally observe the installation guidelines and warranty provisions of the vehicle manufacturer. In any case, you must draw the attention of the customer (vehicle owner) to the installation of an electrical assembly and explain the risks. It is advisable to contact the vehicle manufacturer or one of his authorized workshops in order to rule out any risks.**